

# Installing your new TrojanUVMax™ Power Supply

### **Step 1** - Confirm required components are present

You should have:

1 x Black Power Supply (Including Lamp Harness)



1 x Prepaid Return Shipping Label



Applicable only if you have received this package directly from VIQUA.

#### 1 x Warranty Card

bes of Norteen Secretary Service Adaptation Perform (Adaptate Seagnate)		to control		ten demokracy forth an homocole			
		pay-ann, rate out, le embre	Majdane in Tai di Majdana Salika		and harist area debices		
	Marie Japanese	Pera Labracia, Vincyclin		ally other model	protes	29-10-129-12	
Sealer Stradies Vandels	_	company homographs homostic	Salaybase on Jan de Salaybase Salabase		March Transfel Transa March Stea		
Allian Indiana (Ancida			op/sh/mod		posto (#-01/(#-01		
1 Water Descript Chancer Services ( Major of	del Agent			January most to company mounts	3.71	OTTA	
Control of Spirit (system) (in terms) (in the spirit (system) (in the spirit (				Name is record to proprietate year factors complete to provide.	_ V J	QUA	
I have of the belong "have to believe to "have	-5×65(b)			complete to be being to	47000	MONOCOCK CONTO	
				\$600 NAME OF THE PARTY OF THE P		ir Road West	
O STATE OF THE PARTY OF T					1,519.7	Guelph, CN CA N1L 1R1 L 519 353 3532 L 519 363 5069	
A flow first field an about the prober? Support part constraint have probe? Support constraint of a constraint				Series .			
						Pvique.com	
The state of the contract of the state of th						r.viqua.com	

Applicable only if you have received this package directly from VIQUA.

NOTE: If any of these items are missing please contact VIQUA immediately at 1-800-265-5774

# Step 2 - Remove your existing Power Supply

You will need to first unplug the system from the wall outlet.



- Remove the harness cap and lamp harness from the system.
- Remove the black lamp cover from the cord.





- Using a screwdriver, undo the ground screw releasing both the ground (green) and strain relief (red) lines.
- Using your hands push the power supply upwards to remove it from its mounting bracket.
- Unplug the power cord from the power supply.







# **Step 3** - Install your new Power Supply

Taking the power supply only, gently slide back onto the mounting bracket attached to the wall.



Using a screwdriver, reattach the ground (green) and strain relief (red) to the UV chamber.




Snap the black lamp cover back over the cord.





Attach the lamp harness to the lamp being sure the 2 pronged jumpers are aligned to their contacts on the harness.



(this may take up to

5 mins).





NOTE: If LEDs do not go solid green, consult the troubleshooting section of your manual, or if you have any further questions regarding these instructions, please contact VIQUA at 1-800-265-5774.

## Step 4 - Return Defective Item

Note: Applicable only if you have received this package directly from VIQUA. Return defective item within 7 days to avoid being charged.

- Place defective item into the box of your replacement power supply. Note: the only item that should be returned to VIQUA is the black power supply.
- Remove original shipping label from box and replace with new prepaid shipping label included within this package.
- Please call UPS at 1-800-742-5877 (Canada and US) and follow the voice prompts to arrange for a pick up.

